



GJB13000Ei

PERFORMANCE	
FREQUENCY	50Hz/60Hz
RUNNING WATTS	12000W
PEAK WATTS	13000W
ENGINE	
Engine Brand	Gucbir
Engine Type	Single cylinder, 4-Stroke, OHV, Air Cooled
Displacement (cc)	550cc
Starting Type	Recoil/E-start Start
Fuel Type	Gasoline
Output Speed (RPM)	2800-3600RPM
Run Time @ 50% Load	11-6h
Low Oil Shutdown	yes
25% Load Noise Level (dB@ 7m)	80dB
CONTROL PANEL	
Rated Amperage	43.5AMP
Phase	Single
Outlets	Two 250V 16AMP Outlet, One 5V DC 3.6AMP Outlet /Parallel Sockets/ECO Function
AVR	
Hour Meter (LCD)	Yes
Circuit Breakers	Yes
Rubber Outlet Dust Covers	Yes
OVERALL DESIGN	
Frame Style	Compact Metal Frame
Frame Finish	Antioxidant insulating varnish
Wheel & Tire Type	Yes
Engine Oil Capacity (L)	1.3L
Engine Oil Type	SAE 10W-30
Fuel Tank Size (L)	34L
OTHER GENERATOR FEATURES	
Engine oil bottle	Optional
Accessories	Spark Plug "T" Wrench & Oil Funnel & screwdriver
Battery Type	Lead-acid Battery
Battery Included	Yes
PACKAGING DETAILS	
Outside packing dimensions (mm)(L x W x H)	755*625*655
Net Weight (kg)	83kg
Gross Weight (kg)	88kg