



## GJB4000iS

PERFORMANCE	
FREQUENCY	50Hz
RUNNING WATTS	3600W
PEAK WATTS	4000W
ENGINE	
Engine Brand	Gucbir
Engine Type	Single cylinder, 4-Stroke, OHV, Air Cooled
Displacement (cc)	149cc
Starting Type	<b>Recoil Start</b>
Fuel Type	Gasoline
Output Speed (RPM)	3400-4400
Run Time @ 50% Load	5.5h
Low Oil Shutdown	yes
25% Load Noise Level (dB@ 7m)	65dB
CONTROL PANEL	
Rated Amperage	13AMP
Phase	Single
Outlets	Two 250V 16AMP Outlet, Type A+C/Multifunction Display/ECO Function/Parallel Sockets
AVR	
Hour Meter (LCD)	Yes
Circuit Breakers	Yes
Rubber Outlet Dust Covers	Yes
OVERALL DESIGN	
Frame Style	Compact Carrying Case
Frame Finish	Impact Resistant PP & PA
Wheel & Tire Type	Yes
Engine Oil Capacity (L)	0.48L
Engine Oil Type	SAE 10W-30
Fuel Tank Size (L)	6L
OTHER GENERATOR FEATURES	
Engine oil bottle	Optional
Accessories	Spark Plug "T" Wrench & Oil Funnel
Battery Type	Lead-acid Battery
Battery Included	Yes
PACKAGING DETAILS	
Outside packing dimensions (mm)(L x W x H)	555*405*542
Net Weight (kg)	28kg
Gross Weight (kg)	30.5kg